

Print Driver Installation Guide (Windows)

- 1) [Click Here](#) (This will open a web browser and start downloading the print driver for your device) If you cannot locate the downloaded print drive press ctrl+J to bring up your download's menu in the web browser that was opened.
- 2) Open the KXDRIVER download. Accept the Notice that appears. Press OK on the next box that follows.
- 3) **If you have a pre-existing Kyocera installation on your computer:** You will go to the uninstall feature (bottom option), select the device that you are having issues with, and run the uninstaller. Press Finish when it is completed.
- 4) **For New Installations or Reinstallations:** Run Express Install. Pick the Device using an IPv4 Address in the Details section. Uncheck *FONTS* and *Status Monitor* in the bottom portion of the installer, then press install. See **Example 1** on Next page or visual details.
NOTE: Windows Security May ask for permission to install it, be sure to allow.
- 5) The Finish Screen will appear with more options. Uncheck “*Set Duplex as default*” and “*Show Quick Print tab.*” Select “*Print a test page*” to confirm the device is operating correctly. See **Example 2** on next page for visual details.

Example 1

 **Express Install**
Add single device and its default drivers

Select the device you want to add.

Device	Details
 TASKalfa 7054ci	192.168.30.122
 ECOSYS P6130cdn	192.168.30.148
 ECOSYS P6235cdn	192.168.30.144
 TASKalfa 6052ci	192.168.30.105
 TASKalfa 6053ci	192.168.30.175

5 devices

☐ Use host name as port name

 SNMP Settings 

Select the features you want to use with this device.

Name	Description
☒ KX DRIVER	(Recommended) Extended-functionality printing
☐ FONTS	Screen fonts that match the printer's fonts
☐ Status Monitor 5	Advanced service for monitoring current printer status

Back

Install

Exit

Example 2

 Kyocera Product Library 

Finished

Your software is ready to use.

Product	Details
 KX DRIVER	Installed...Kyocera TASKalfa 6053ci KX
 Uninstaller	Installed



   **Print a test page**

   Set Duplex as default

   Show Quick Print tab

Finish